

Въведете: **192 . 168 . 0 . 152 / 26** SubNet брой IP **64**
mask 255 . 255 . 255 . 192 next 192

№ **7** ЙОРДАН Р. ЙОРДАНОВ

	IP	Bit	№
ID sub net	192 . 168 . 0 . 128 /	29	1
Gateway (1 host) шлюз	192 . 168 . 0 . 129	132	
Last host	192 . 168 . 0 . 134		
Broadcast	192 . 168 . 0 . 135		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 136 /	29	2
Gateway (1 host) шлюз	192 . 168 . 0 . 137	140	
Last host	192 . 168 . 0 . 142		
Broadcast	192 . 168 . 0 . 143		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 144 /	29	3
Gateway (1 host) шлюз	192 . 168 . 0 . 145	148	
Last host	192 . 168 . 0 . 150		
Broadcast	192 . 168 . 0 . 151		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 152 /	29	4
Gateway (1 host) шлюз	192 . 168 . 0 . 153	156	
Last host	192 . 168 . 0 . 158		
Broadcast	192 . 168 . 0 . 159		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 160 /	29	5
Gateway (1 host) шлюз	192 . 168 . 0 . 161	164	
Last host	192 . 168 . 0 . 166		
Broadcast	192 . 168 . 0 . 167		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 168 /	29	6
Gateway (1 host) шлюз	192 . 168 . 0 . 169	172	
Last host	192 . 168 . 0 . 174		
Broadcast	192 . 168 . 0 . 175		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 176 /	29	7
Gateway (1 host) шлюз	192 . 168 . 0 . 177	180	
Last host	192 . 168 . 0 . 182		
Broadcast	192 . 168 . 0 . 183		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		
ID sub net	192 . 168 . 0 . 184 /	29	8
Gateway (1 host) шлюз	192 . 168 . 0 . 185	188	
Last host	192 . 168 . 0 . 190		
Broadcast	192 . 168 . 0 . 191		
mask sub net	255 . 255 . 255 . 248		
брой IP sub net	8		
брой host sub net	6		